

BM1606 - Cashiering Station Utility Screen

Use the Cashiering Station Utility Screen to configure and test cashiering stations.

User Function Keys

F1	REFRESH	Redisplays the screen. Any additions or changes you made since you last pressed Enter will disappear.
F2	PRINTER TEST	Initiates a self-test by a slip printer. An 8.5 x 11-inch piece of paper is required. This function key is only displayed if a properly configured slip printer is attached to the cashiering station.
	or	
	OPEN DRAWER 1	Opens cash register drawer number 1. This function key is only displayed if a properly configured slip printer is attached to the cashiering station and your access level is 1 or higher.
	or	
	CONFIG DEVICE	Configures the logical device (LDEV) number used to identify a cashiering device. Only the current device can be configured, but you can choose which LDEV number you want to use. This function key is only displayed if the device is a PC running Reflection terminal software and your access level is 2 or higher.
F3	DOWNLOAD CMD FILE	Downloads the current version of the cashiering command file or files to the current device. You can use this function key to configure a new cashiering device.
	or	
	RECEIPT TEST	Prints a sample receipt on a slip printer. This function key is only displayed if a properly configured slip printer is attached to the cashiering station.
	or	
	OPEN DRAWER 2	Opens cash register drawer number 2. This function key is only displayed if a properly configured slip printer is attached to the cashiering station and your access level is 1 or higher.
F4	LIST	Displays a list of all the currently configured cashiering LDEVs and when they were last used. This includes the device number, logon date, logon time, and the session number.
	or	
	RESTART LIST	Re-displays a list of all currently configured cashiering LDEVs and when they were last used. This includes the device number, logon date, logon time, and the session number.
	or	

	ENDORSE TEST	Prints a sample endorsement on a slip printer. This function key is only displayed if a properly configured slip printer is attached to the cashiering station.
F5	DECONFIG DEVICE	Deconfigures a cashiering LDEV number. <ul style="list-style-type: none"> • When your current device is deconfigured, it is completely deconfigured. • When a remote device is deconfigured, only the HP3000 portion is processed. Future attempts to access the remote device will generate error messages indicating that it has been deconfigured. This function key is only displayed if your access level is 3 or higher.
F6	NEXT KEYS	Displays the next available set of function keys. The keys are divided into three groups: <ul style="list-style-type: none"> • Printer keys: Printer Test, Receipt Test, and Endorse Test • Drawer keys: Open Drawer 1 and Open Drawer 2 • Configuration keys: Config Device, Download CMD File, List, Restart List, and Deconfig Device This function key is only displayed if a properly configured slip printer is attached to the cashiering station.
F8	MENU	Redisplays the FMS System Menu.

Using the Screen

Action	Notes
Displaying Device Status	When you access the Cashiering Station Utility Screen (BM1606) from the FMS System Menu, the status of the current device is displayed. <ul style="list-style-type: none"> • To re-display the status, Press F1 (Refresh). • To re-check the status (for example, after changing printer configurations or turning on a slip printer), press Enter when the status screen is displayed.
Testing the Printer	To test the printer, press one of the three printer test keys: F2 (Printer Test), F3 (Receipt Test), or F4 (Endorse Test). These function keys are only displayed if a properly configured slip printer is attached to the PC.
Testing the Cash Drawers	To test the cash register drawers, press one of the cash drawer keys: F2 (Open Cash Drawer 1) or F3 (Open Cash Drawer 2). Note: Not all cashiering stations have multiple cash drawers; however, both keys are displayed even though they may not perform an action. These function keys are only displayed if a properly configured slip printer is attached to the PC.

Configuring a Device	<p>Configuring a cashiering device attaches a unique LDEV number to its cashiering station.</p> <p>To configure a cashiering device:</p> <ol style="list-style-type: none"> 1. Press F2 (Config Device). 2. Type a unique LDEV number. If you leave the field blank, a LDEV number will automatically be assigned. 3. Press Enter.
Deconfiguring a Device	<p>Deconfiguring a cashiering device removes the unique LDEV number from its cashiering station. Only deconfigure cashiering devices that are no longer used.</p> <p>To deconfigure a cashiering device:</p> <ol style="list-style-type: none"> 1. Press F5 (Deconfig Device). 2. Type the LDEV number of the device you want to deconfigure. 3. Press Enter. 4. To confirm that the device is deconfigured, press Enter again. <p>Note: By default, the LDEV number to deconfigure is for the current device.</p> <ul style="list-style-type: none"> • If selected, the LDEV number will be completely deconfigured on the HP3000 and on your PC. • If you choose another LDEV number, it will be deconfigured on the HP3000, but not on the device itself. • If the deconfigured device is used for cashiering in the future, an invalid configuration error will occur.
Configuring a Cashiering Station	<p>Before a device can be used as a cashiering station with a slip printer, it must have the appropriate Reflection command file or files installed.</p> <p>To install the current version of the Reflection command file or files, press F3 (Download CMD File). This process will create the appropriate directory.</p>
Listing Configured Cashiering Devices	<p>To display all currently configured devices and their most recent sessions, press F4 (List) or F4 (Restart List).</p> <p>To view multiple pages in a list, press Enter.</p>

Data Fields

CASHIERING DEVICE (display only)	PRINTER PORT (display only)
HP3000 LOGICAL DEVICE (display only)	CASH DRAWER 1 STATUS (display only)
COMMUNICATIONS PORT (display only)	CASH DRAWER 2 STATUS (display only)
TERMINAL TYPE (display only)	DOCUMENT STATUS (display only)

EMULATOR (display only)	DEVICE TO DECONFIGURE
BM1881RC FILE VERSION (display only)	NEW DEVICE
SLIP PRINTER STATUS (display only)	

Cashiering Device

Definition	Display only. A logical device (LDEV) number used to identify a cashiering device. Note: If the device is not configured, or if a configuration error occurs, a BM1824 message appears to the right of the LDEV number.
Length	3 digits

HP3000 Logical Device

Definition	Display only. A LDEV number the HP3000 system assigns to a cashiering session. Text describing the type of device (hardwired, modem, network) appears to the right of the LDEV number.
Length	3 digits

Communications Port

Definition	Display only. A code identifying the communications port or method that Reflection software uses.
Length	20 characters

Terminal Type

Definition	Display only. A code identifying the type of terminal being emulated.
Length	6 characters

Emulator

Definition	Display only. The emulator (Reflection or Minisoft) and the version (if available) being used.
-------------------	--

BM1881RC File Version

Definition	Display only. The version number of the currently installed cashiering command file or files. Note: If different from the current available version, a message appears to the right of the file version number indicating which version is available.
-------------------	---

Slip Printer Status

Definition	Display only. A code indicating a slip printer's response to a status request. This field is primarily used by SBCTC-ITD staff to research printer problems. Note: When applicable, a corresponding BM1881 message about a slip printer's status appears to the right of the slip printer status code.
Length	2 characters

Printer Port

Definition	Display only. A code identifying the communications port a slip printer uses.
Length	20 characters

Cash Drawer 1 Status

Definition	Display only. A code indicating whether cash drawer number 1 is open or closed. Note: If a device does not have a cash drawer, the code will indicate it is open.
Length	6 characters

Cash Drawer 2 Status

Definition	Display only. A code indicating whether cash drawer number 2 is open or closed. Note: If a device does not have a cash drawer, the code will indicate it is open.
Length	6 characters

Document Status

Definition	Display only. A code indicating whether or not a document is printing on a slip printer.
Length	8 characters

Device to Deconfigure

Definition	The LDEV number that you want to deconfigure.
Length	3 digits

New Device

Definition	The LDEV number assigned to the current device.
Length	3 digits